



AC BACK BOX DETAILS






TV SWITCH BOARD DETAILS

GENERAL NOTE :-

1. ALL BRACKET LIGHTS IN TOILET @ 2100 MM FROM SLAB.
2. ALL BRACKET LIGHTS @2150MM FROM SLAB EXCEPT UTILITY AREA.
3. ALL BRACKET LIGHTS IN UTILITY AREA TO BE 150MM ABOVE BEAM BOTTOM (REFER ELEVATION).
4. ALL CEILING/WALL ROSE @ 2100 MM FROM SLAB.
5. ALL HEIGHTS FROM SLAB.
6. ALL GARDEN WALL BRACKETS TO BE AT 900 FROM PLINTH LEVEL.
7. ALL SET-OUT DIMENSIONS FOR SB ARE FOR FINISHED SB PLATE.
8. ***FOR DOLPHIN PELMET, AC BACK BOX LOCATION TO BE ESTABLISHED ON PELMET OUTER SURFACE AND COVERED WITH BLANK PLATE.***

LEGEND

	CEILING FAN		EXHAUST FAN
	CEILING LIGHT		FIRE ALARM SOUNDER/HOOTER
	WALL BRACKET	MP	MANUAL CALLPOINT
	AIR CONDITIONER		ACCESS POINT
	WALL BRACKET/CORRIDOR		DOME CAMERA
	CONCEALED CEILING ROSE		GARDEN WALL BRACKET
	FIRE PANEL	6A	6 AMP SWITCH + SOCKET



DETAILS FOR BRACKET LIGHTS IN UTILITY AREA

PALAVA,LAKEFRONT - FLOREA A,B WING
1 BHK - STUDIO
FLOREA_A - (UNIT 6)
FLOREA_D - (UNIT 6)

SR.NO	SR.NO	POINT CONTROL	MODULES	HT. OF SB (BTM OF SB FROM SL)	REMARKS
ENTRANCE					
L-01	1	BELL POINT	1	1400MM	
LIVING/DINING					
L-02	1	BL-1	1	1250MM	
	2	F-1 (ONLY REGULATOR)	2		
	3	6 A SOCKET WITH SWITCH	3		
L-03	1	CL-C	1	600MM	TO BE PLACED IN 2 NOS OF 6/8 MODULE BOARDS INSTEAD OF ONE LARGE 10*12 MODULE SQUARE BOX
	2	F-2 (ONLY REGULATOR)	2		
	3	BL-2	3		
	4	AC (SWITCH)	4		
	5	6 A - 2 SOCKETS WITH 2 SWITCH	5		
	6	TELEPHONE POINT	6		
	7	INTERCOM	7		
	8	GARDEN BRACKET LIGHT	8		
L-04	1	TV	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 2 SOCKETS WITH 2 SWITCH	2		
	3	DATA	3		
	4	6 A TV SOCKET	4		
L-05A	1	CL-2	1	2250MM	
PASSAGE					
PASSAGE BOX		BELL CHIMER	1	1950MM (TOP OF DB)	
KITCHEN & UTILITY					
K-01	1	CL-2	1	1250MM	
	2	CL-C	2		
	3	F-2 (ONLY REGULATOR)	3		
	4	BL-2	4		
	5	EXHAUST FAN	5		
	6	6 A SOCKET & SWITCH (GENERAL)	6		
K-02	1	16 A SOCKET WITH SWITCH FOR REFRIGERATOR	3	1250MM	
K-03	1	16 A SOCKET & SWITCH FOR MICROWAVE	3	1250MM	
K-04	1	6 A SOCKET WITH SWITCH FOR WATER PURIFIER	3	1900MM	
K-05	1	16 A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
COMMON TOILET					
T-01	1	BL-4	1		
	2	BL-5	2		
	3	GEYSER (SWITCH WITH INDICATOR)	3	1250MM	
	4	EXHAUST FAN	4		
	5	6 A SOCKET WITH SWITCH	5		
T-02	1	16 A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
T-03	1	20 A SOCKET FOR GEYSER	2	2100MM	
BEDROOM 01					
POWER & ELU DB				1950MM (TOP OF DB)	
BR-01	1	CL- 3	1	1250MM	
BR-02	1	TV POINT	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 1 SOCKET WITH 1 SWITCH	2		
BR-2A	1	6 A TV SOCKET	1	600MM	
BR-03	1	CL-4	1		
	2	F-4 (ON-1 REGULATOR)	2		
	3	6 A SOCKET WITH SWITCH	3	600MM	
BR-04	1	AC (SWITCH)	2		
	2	6 A SOCKET WITH SWITCH	3	600MM	
BR-05	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
BR-06	1	BL-3	1	1250MM	
	2	F-3 (ON-1 REGULATOR)	2		

PALAVA,LAKEFRONT - FLOREA A,B WING
1 BHK MODIFIED
FLOREA_A - (UNIT 4 & 7)
FLOREA_D - (UNIT 8)

SR.NO	SR.NO	POINT CONTROL	MODULES	HT. OF SB (BTM OF SB FROM SL)	REMARKS
ENTRANCE					
L-01	1	BELL POINT	1	1400MM	
LIVING/DINING					
L-02	1	BL-1	1	1250MM	
	2	F-1 (ONLY REGULATOR)	2		
	3	6 A SOCKET WITH SWITCH	3		
L-03	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM	
L-04	1	CL-1	1	600MM	TO BE PLACED IN 2 NOS OF 6/8 MODULE BOARDS INSTEAD OF ONE LARGE 10*12 MODULE SQUARE BOX
	2	F-2 (ONLY REGULATOR)	2		
	3	BL-2	3		
	4	AC (SWITCH)	4		
	5	6 A - 2 SOCKETS WITH 2 SWITCH	5		
	6	TELEPHONE POINT	6		
	7	INTERCOM	7		
	8	GARDEN BRACKET LIGHT	8		
L-05	1	TV	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 2 SOCKETS WITH 2 SWITCH	7		
	3	DATA	8		
	4	6 A TV SOCKET	9	600MM	
L-05A	1	CL-2	1	1250MM	
PASSAGE					
POWER & ELU DB BOX		BELL CHIMER	1	1950MM (TOP OF DB) 1950 MM (TOP)	
KITCHEN & UTILITY					
K-01	1	CL-2	1	1250MM	
	2	CL-C	2		
	3	F-2 (ONLY REGULATOR)	3		
	4	BL-2	4		
	5	EXHAUST FAN	5		
	6	6 A SOCKET & SWITCH (GENERAL)	6		
K-02	1	16 A SOCKET WITH SWITCH FOR REFRIGERATOR	3	1250MM	
K-03	1	16 A SOCKET & SWITCH FOR MICROWAVE	3	1250MM	
K-04	1	6 A SOCKET WITH SWITCH FOR WATER PURIFIER	3	1900MM	
K-05	1	16 A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
COMMON TOILET					
T-01	1	BL-4	1		
	2	BL-5	2		
	3	GEYSER (SWITCH WITH INDICATOR)	3	1250MM	
	4	EXHAUST FAN	4		
	5	6 A SOCKET WITH SWITCH	5		
T-02	1	20 A SOCKET FOR GEYSER	2	2100MM	
MASTER BEDROOM					
MB-01	1	CL-4	1	1250MM	
MB-02	1	CL-5	1		
	2	F-4 (ONLY REGULATOR)	2	600MM	
	3	6 A SOCKET WITH SWITCH	3		
MB-03	1	AC (SWITCH)	2	600MM	
	2	6 A SOCKET WITH SWITCH	3		
MB-04	1	TV POINT	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 1 SOCKET WITH 1 SWITCH	2		
MB-04A	1	6 A TV SOCKET	1	600MM	
MB-05	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM	
MASTER TOILET					
MT-01	1	BL-7	1	1250MM	
	2	BL-6	2		
	3	GEYSER (SWITCH WITH INDICATOR)	3		
	4	EXHAUST FAN	4		
	5	6 A SOCKET WITH SWITCH	5		
MT-02	1	20 A SOCKET FOR GEYSER	2	2100MM	

PALAVA,LAKEFRONT - FLOREA A,B WING
1 BHK
FLOREA_A - (UNIT 2 & 5)
FLOREA_D - (UNIT 5 & 9)

SR.NO	SR.NO	POINT CONTROL	MODULES	HT. OF SB (BTM OF SB FROM SL)	REMARKS
LIVING/DINING					
L-02	1	BL-1	1	1250MM	
	2	F-1 (ONLY REGULATOR)	2		
	3	6 A SOCKET WITH SWITCH	3		
L-03	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM	
L-04	1	CL-1	1	600MM	TO BE PLACED IN 2 NOS OF 6/8 MODULE BOARDS INSTEAD OF ONE LARGE 10*12 MODULE SQUARE BOX
	2	F-2 (ONLY REGULATOR)	2		
	3	BL-2	3		
	4	AC (SWITCH)	4		
	5	6 A - 2 SOCKETS WITH 2 SWITCH	5		
	6	TELEPHONE POINT	6		
	7	INTERCOM	7		
	8	GARDEN BRACKET LIGHT	8		
L-05	1	TV	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 2 SOCKETS WITH 2 SWITCH	7		
	3	DATA	8		
	4	6 A TV SOCKET	9	600MM	
L-05A	1	CL-2	1	1250MM	
PASSAGE					
PASSAGE BOX		BELL CHIMER	1	1950MM (TOP OF DB) 1950MM (TOP)	
KITCHEN & UTILITY					
K-01	1	CL-2	1	1250MM	
	2	CL-C	2		
	3	F-2 (ONLY REGULATOR)	3		
	4	BL-2	4		
	5	EXHAUST FAN	5		
	6	6 A SOCKET & SWITCH (GENERAL)	6		
K-02	1	16 A SOCKET WITH SWITCH FOR REFRIGERATOR	3	1250MM	
K-03	1	16 A SOCKET & SWITCH FOR MICROWAVE	3	1250MM	
K-04	1	6 A SOCKET WITH SWITCH FOR WATER PURIFIER	3	1900MM	
K-05	1	16 A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
COMMON TOILET					
T-01	1	BL-4	1		
	2	BL-5	2		
	3	GEYSER (SWITCH WITH INDICATOR)	3	1250MM	
	4	EXHAUST FAN	4		
	5	6 A SOCKET WITH SWITCH	5		
T-02	1	20 A SOCKET FOR GEYSER	2	2100MM	
MASTER BEDROOM					
MB-01	1	CL-5	1	1250MM	
MB-02	1	F-4 (ONLY REGULATOR)	2	600MM	
	2	6 A SOCKET WITH SWITCH	3		
MB-03	1	AC (SWITCH)	2	600MM	
	2	6 A SOCKET WITH SWITCH	3		
	3	CL-6	1		APPLICABLE FOR MASTER BEDROOM WITH PRIVATE GARDEN
	4	GARDEN BRACKET LIGHT	1		
MB-04	1	TV POINT	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 1 SOCKET WITH 1 SWITCH	5		
MB-04A	1	6 A TV SOCKET	1	600MM	
MB-05	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM	
MASTER TOILET					
MT-01	1	BL-7	1	1250MM	
	2	BL-6	2		
	3	GEYSER (SWITCH WITH INDICATOR)	3		
	4	EXHAUST FAN	4		
	5	6 A SOCKET WITH SWITCH	5		
MT-02	1	20 A SOCKET FOR GEYSER	2	2100MM	

PALAVA,LAKEFRONT - FLOREA A,B WING
2 BHK
FLOREA_A - (UNIT 3)
FLOREA_D - (UNIT 3 & 7)


SR.NO	SR.NO	POINT CONTROL	MODULES	HT. OF SB (BTM OF SB FROM SL)	REMARKS
LIVING-DINING					
L-02	1	BL-1	1	1250MM	
	2	F-1 (ONLY REGULATOR)	2		
	3	6 A SOCKET WITH SWITCH	3		
L-03	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
L-04	1	CL-1	1	600MM	TO BE PLACED IN 2 NOS OF 6/8 MODULE BOARDS INSTEAD OF ONE LARGE 10*12 MODULE SQUARE BOX
	2	F-2 (ONLY REGULATOR)	2		
	3	BL-2	3		
	4	AC (SWITCH)	4		
	5	6 A - 2 SOCKETS WITH 2 SWITCH	5		
	6	TELEPHONE POINT	6		
	7	INTERCOM	7		
	8	GARDEN BRACKET LIGHT	8		
L-05	1	TV	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 2 SOCKETS WITH 2 SWITCH	7		
	3	DATA	8		
	4	6 A TV SOCKET	9	600MM	
L-05A	1	CL-2	1	1250MM	
PASSAGE					
PASSAGE BOX		BELL CHIMER	1	1950MM (TOP OF DB) 1950MM (TOP)	
KITCHEN & UTILITY					
K-01	1	CL-2	1	1250MM	
	2	CL-C	2		
	3	F-2 (ONLY REGULATOR)	3		
	4	BL-2	4		
	5	EXHAUST FAN	5		
	6	6 A SOCKET & SWITCH (GENERAL)	6		
K-02	1	16 A SOCKET WITH SWITCH FOR REFRIGERATOR	3	1250MM	
K-03	1	16 A SOCKET & SWITCH FOR MICROWAVE	3	1250MM	
K-04	1	6 A SOCKET WITH SWITCH FOR WATER PURIFIER	3	1900MM	
K-05	1	16 A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
COMMON TOILET					
T-01	1	BL-4	1		
	2	BL-5	2		
	3	GEYSER (SWITCH WITH INDICATOR)	3	1250MM	
	4	EXHAUST FAN	4		
	5	6 A SOCKET WITH SWITCH	5		
T-02	1	20 A SOCKET FOR GEYSER	2	2100MM	
BEDROOM 01					
BR-01	1	CL-4	1	1250MM	
BR-02	1	CL-5	1		
	2	F-4 (ONLY REGULATOR)	2	600MM	
	3	6 A SOCKET WITH SWITCH	3		
BR-03	1	AC (SWITCH)	2	600MM	
	2	6 A SOCKET WITH SWITCH	3		
	3	GARDEN BRACKET LIGHT	1		
BR-04	1	TV POINT	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 1 SOCKET WITH 1 SWITCH	2		
BR-04A	1	6 A TV SOCKET	1	600MM	
BR-05	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
MASTER BEDROOM					
MB-01	1	CL-6	1	1250MM	
MB-02	1	CL-7	1		
	2	F-6 (ON-1 REGULATOR)	2	600MM	
	3	6 A SOCKET WITH SWITCH	3		
	4	BL-5	4		
MB-03	1	CL-8	1		
	2	AC (SWITCH)	2	600MM	
	3	6 A SOCKET WITH SWITCH	3		
	4	GARDEN BRACKET LIGHT	1		
MB-04	1	TV POINT	1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
	2	6 A - 1 SOCKET WITH 1 SWITCH	2		
MB-04A	1	6 A TV SOCKET	1	600MM	
MB-05	1	20A A C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
MASTER TOILET					
MT-01	1	BL-7	1	1250MM	
	2	BL-6	2		
	3	GEYSER (SWITCH WITH INDICATOR)	3		
	4	EXHAUST FAN	4		
	5	6 A SOCKET WITH SWITCH	5		
MT-02	1	20 A SOCKET FOR GEYSER	2	2100MM	

FLOREA WING A

GENERAL NOTES

1 : All dimensions are in millimeters and levels in meters unless specified otherwise.
2 : Do not scale the drawing; follow written dimensions.
3 : All dimensions are unfinished dimensions unless specified otherwise.
4 : Any discrepancies should be brought to the notice of the Architect prior to execution of job / procuring materials at site.
5 : This drawing is the property of Kapadia Associates and should not be reproduced, copied, handed over to a third party or used for any purpose other than for which it has been issued.
6 : This drawing is to be read in conjunction with all relevant structural & services drawings.

KEY PLAN



REVISION INDEX

REV.NO.	DATE	DESCRIPTION
R-00	18-03-2019	
R-01	29-03-2019	SB DETAIL DIAGRAM FOR T.V ADDED CONTROL MODULE ADDED NEXT TO MCP DB LOCATION REVISED IN APARTMENT NO. 6

CONSULTANTS

GOKANI CONSULTANTS
Structural Consultants
Tel : +919222638004/6400
email : info@gokaniconsultants.com

MICRO ENGINEERING
MEP Consultants
Tel : 0120-4558718
email : business@meindia.com

PBB
Planner/ Landscape Architect
Tel : 079 6923054
email : landscapeindia@usg.net

STAMP & SIGN

PROJECT TITLE	PROJ.NO
PALAVA- LAKEFRONT	**L-10518**
DRAWING TITLE	**DWG.NO**
AR-FLOREA A_GROUND FLOOR ELECTRICAL PLAN	**801.1**
DRAWING STAGE	**REV.NO**
WORKING DRAWING	**R-01**

DRAWN	CHECKED	SCALE	DATE
AD	ES	1:50	24-04-2019

KAPADIA ASSOCIATES
architecture urban design
112-114, Peninsula Centre,Dr. S.S. Rao Road, Nr.Ambedkar Road,Parel East, Mumbai 400012
Tel : 91-22-6660 2638 / 39
Fax : 91-22-6660 2644
Email : kapa@vsnl.in
Website : www.vsnl.in