

PALAVA/LAKEFRONT - FLOREA/A & D WING

1 BHK - STUDIO

FLOREA_A - (UNIT 6, 7)

FLOREA_D - (UNIT 6)

SR NO	POINT CONTROL	MODULES	HT. OF SB (BTM OF SB FROM SL)	REMARKS
ENTRANCE				
L-01	1 BELL POINT	1	1400MM	
LIVING-DINING				
L-02	1 BL-1 2 F-1 (ONLY REGULATOR) 3 6-A SOCKET WITH SWITCH	1 2 3	1250MM	
L-03	1 CL-1 2 F-2 (ONLY REGULATOR) 3 BL-2 4 AC (SWITCH) 5 6-A / 2 SOCKETS WITH 2 SWITCH 6 TELEPHONE POINT 7 INTERCOM 8 GARDEN BRACKET LIGHT	1 2 2 2 6 1 1	600MM	TO BE PLACED IN 2 ROWS OF 6/8 MODULE BOARDS NOTICE OF USE LARGE 10*12 MODULE SQUARE BOX
L-04	1 T.V 2 6-A / 2 SOCKETS WITH 2 SWITCH 3 DATA 4 6-A TV SOCKET	1 2 1 1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
L-04A	1 6-A TV SOCKET	1	850MM	
L-05	1 20A A.C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
PASSAGE				
P-01 POWER & ELV DB BOX	BELL CHIMER	1	1250MM 1600MM (TOP OF DB) 1800 MM (TOP)	
KITCHEN & UTILITY				
K-01	BELL CHIMER		1900 MM (TOP)	
K-01	1 BL-2 2 6-A SOCKET & SWITCH (GENERAL) 3 16-A SOCKET WITH SWITCH FOR REFRIGERATOR	1 3 3		
K-02	1 16-A SOCKET & SWITCH FOR MICROWAVE	3	1250MM	
K-03	1 6-A SOCKET WITH SWITCH FOR WATER PURIFIER 2 EXHAUST FAN	3	1600MM	
COMMON TOILET				
T-01	1 BL-5 2 BL-6 3 GEYSER (SWITCH WITH INDICATOR) 4 EXHAUST FAN 5 6-A SOCKET WITH SWITCH	1 1 3 1 3	1250MM	
T-02	1 16-A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
T-03	1 20-A SOCKET FOR GEYSER	2	2100MM	
BEDROOM 01				
POWER & ELV DB			1800MM (TOP OF DB)	
BR-01	1 CL-3	1	1250MM	
BR-02	1 TV POINT 2 6-A / 1 SOCKET WITH 1 SWITCH	1 5	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
BR-2A	1 6-A TV SOCKET	1	850MM	
BR-03	1 CL-4 2 F-4 (ONLY REGULATOR) 3 6-A SOCKET WITH SWITCH	1 2 3	600MM	
BR-04	1 AC (SWITCH) 2 6-A SOCKET WITH 1 SWITCH	2 3	600MM	
BR-05	1 20A A.C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
BR-06	1 BL-3 2 F-5 (ONLY REGULATOR)	1 2	1250MM	

PALAVA/LAKEFRONT - FLOREA/A & D WING

1 BHK MODIFIED

FLOREA_A- (UNIT 6 & 7)

FLOREA_D - (UNIT 6)

SR NO	POINT CONTROL	MODULES	HT. OF SB (BTM OF SB FROM SL)	REMARKS
ENTRANCE				
L-01	1 BELL POINT	1	1400MM	
LIVING-DINING				
L-02	1 BL-1 2 F-1 (ONLY REGULATOR) 3 6-A SOCKET WITH SWITCH	1 2 3	1250MM	
L-03	1 20A A.C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM	
L-04	1 CL-1 2 F-2 (ONLY REGULATOR) 3 BL-2 4 AC (SWITCH) 5 6-A / 2 SOCKETS WITH 2 SWITCH 6 TELEPHONE POINT 7 INTERCOM 8 GARDEN BRACKET LIGHT	1 2 2 2 6 1 1	600MM	TO BE PLACED IN 2 ROWS OF 6/8 MODULE BOARDS NOTICE OF USE LARGE 10*12 MODULE SQUARE BOX
L-05	1 T.V 2 6-A / 2 SOCKETS WITH 2 SWITCH 3 DATA 4 6-A TV SOCKET	1 2 1 1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
L-05A	1 6-A TV SOCKET	1	850MM	
PASSAGE				
P-01 ELEC. & ELV. DB BOX	CL-7 BELL CHIMER	1	1250MM 1600MM (TOP OF DB) 1800 MM (TOP)	
KITCHEN & UTILITY				
K-01	CL-2 CL-5 F-3 (ONLY REGULATOR) BL-2 EXHAUST FAN 6-A SOCKET & SWITCH (GENERAL)	1 1 3 1 1 3	1250MM	
K-02	1 16-A SOCKET WITH SWITCH FOR REFRIGERATOR	3	1250MM	
K-03	1 16-A SOCKET & SWITCH FOR MICROWAVE	3	1250MM	
K-04	1 6-A SOCKET WITH SWITCH FOR WATER PURIFIER	3	1600MM	
K-05	1 16-A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
COMMON TOILET				
T-01	1 BL-6 2 BL-5 3 GEYSER (SWITCH WITH INDICATOR) 4 EXHAUST FAN 5 6-A SOCKET WITH SWITCH	1 1 3 1 3	1250MM	
T-02	1 20-A SOCKET FOR GEYSER	2	2100MM	
MASTER BEDROOM				
MB-01	1 CL-6	1	1250MM	
MB-02	1 F-4 (ONLY REGULATOR) 2 6-A SOCKET WITH SWITCH	2 3	600MM	
MB-03	1 AC (SWITCH) 2 6-A SOCKET WITH SWITCH 3 CL-8	2 3 1	600MM	APPLICABLE FOR MASTER BEDROOM WITH PRIVATE GARDEN
	4 GARDEN BRACKET LIGHT	1		
MB-04	1 TV POINT 2 6-A / 1 SOCKET WITH 1 SWITCH	1 5	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
MB-04A	1 6-A TV SOCKET	1	850MM	
MB-05	1 20A A.C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM	
MASTER TOILET				
MT-01	1 BL-4 2 BL-5 3 GEYSER (SWITCH WITH INDICATOR) 4 EXHAUST FAN 5 6-A SOCKET WITH SWITCH	1 1 3 1 3	1250MM	
MT-02	1 20-A SOCKET FOR GEYSER	2	2100MM	


PALAVA/LAKEFRONT - FLOREA/A & D WING

2 BHK


FLOREA_A- (UNIT 3)

FLOREA_D - (UNIT 3 & 5)


SR NO	POINT CONTROL	MODULES	HT. OF SB (BTM OF SB FROM SL)	REMARKS
LIVING-DINING				
L-02	1 BL-1 2 F-1 (ONLY REGULATOR) 3 6-A SOCKET WITH SWITCH	1 2 3	1250MM	
L-03	1 20A A.C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM	
L-04	1 CL-1 2 F-2 (ONLY REGULATOR) 3 BL-2 4 AC (SWITCH) 5 6-A / 2 SOCKETS WITH 2 SWITCH 6 TELEPHONE POINT 7 INTERCOM 8 GARDEN BRACKET LIGHT	1 2 2 2 6 1 1	600MM	TO BE PLACED IN 2 ROWS OF 6/8 MODULE BOARDS NOTICE OF USE LARGE 10*12 MODULE SQUARE BOX
L-05	1 T.V 2 6-A / 2 SOCKETS WITH 2 SWITCH 3 DATA 4 6-A TV SOCKET	1 2 1 1	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
L-05A	1 6-A TV SOCKET	1	850MM	
PASSAGE				
P-01 ELEC. & ELV. DB BOX	CL-9 CL-8A BELL CHIMER	1 1 1	1250MM 1600MM (TOP OF DB) 1800 MM (TOP)	
KITCHEN & UTILITY				
K-01	CL-2 CL-5 F-3 (ONLY REGULATOR) BL-2 EXHAUST FAN 6-A SOCKET & SWITCH (GENERAL)	1 1 3 1 1 3	1250MM	
K-02	1 16-A SOCKET WITH SWITCH FOR REFRIGERATOR	3	1250MM	
K-03	1 16-A SOCKET & SWITCH FOR MICROWAVE	3	1250MM	
K-04	1 6-A SOCKET WITH SWITCH FOR WATER PURIFIER	3	1600MM	
K-05	1 16-A SOCKET WITH SWITCH FOR WASHING MACHINE	3	1250MM	
COMMON TOILET				
T-01	1 BL-6 2 BL-5 3 GEYSER (SWITCH WITH INDICATOR) 4 EXHAUST FAN 5 6-A SOCKET WITH SWITCH	1 1 3 1 3	1250MM	
T-02	1 20-A SOCKET FOR GEYSER	3	2100MM	
BEDROOM 01				
BR-01	1 CL-4	1	1250MM	
BR-02	1 CL-3 2 F-5 (ONLY REGULATOR) 3 6-A SOCKET WITH SWITCH	1 2 3	600MM	
BR-2A	1 AC (SWITCH) 2 6-A SOCKET WITH SWITCH	2 3	600MM	
BR-3A	1 TV POINT 2 6-A / 1 SOCKET WITH 1 SWITCH	1 5	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
BR-3AA	1 6-A TV SOCKET	1	850MM	
BR-3B	1 20A A.C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
MASTER BEDROOM				
MB-02	1 CL-8	1	1250MM	
MB-02	1 CL-7 2 F-4 (ONLY REGULATOR) 3 6-A SOCKET WITH SWITCH 4 BL-1	1 2 3 1	600MM	
MB-03	1 AC (SWITCH) 2 6-A SOCKET WITH SWITCH 3 GARDEN BRACKET LIGHT	2 3 1	600MM	
MB-04	1 TV POINT 2 6-A / 1 SOCKET WITH 1 SWITCH	1 5	600MM	STB + TV ON SINGLE SWITCH (REFER KEY ELEVATION)
MB-04A	1 6-A TV SOCKET	1	850MM	
MB-05	1 20A A.C BACK BOX	2	+250MM FROM BEAM BOTTOM(150 BEAM DEPTH)	
MASTER TOILET				
MT-01	1 BL-7 2 BL-8 3 GEYSER (SWITCH WITH INDICATOR) 4 EXHAUST FAN 5 6-A SOCKET WITH SWITCH	1 1 3 1 3	1250MM	
MT-02	1 20-A SOCKET FOR GEYSER	3	2100MM	




DETAILS FOR BRACKET LIGHTS IN UTILITY AREA



AC BACK BOX DETAILS





SB 1

TV SWITCH BOARD DETAILS

GENERAL NOTE :-

1. ALL BRACKET LIGHTS IN TOILET @ 2100 MM FROM SLAB.
2. ALL BRACKET LIGHTS @2100MM FROM SLAB EXCEPT UTILITY AREA.
3. ALL BRACKET LIGHTS IN UTILITY AREA TO BE 1500MM ABOVE BEAM BOTTOM (REFER ELEVATION)
4. ALL CEILING/WALL ROSE @ 2100 MM FROM SLAB.
5. ALL HEIGHTS FROM SLAB.
6. ALL GARDEN WALL BRACKETS TO BE AT 900 FROM PLINTH LEVEL.
7. ALL SET OUT DIMENSIONS FOR SB ARE FOR FINISHED SB PLATE.
8. ***FOR DGs ON PELMET, AC BACK BOX LOCATION TO BE ESTABLISHED ON PELMET OUTER SURFACE AND COVERED WITH BLANK PLATE.***


LEGEND			
	CEILING FAN		EXHAUST FAN
	CEILING LIGHT		FIRE ALARM SOUNDER/HOOTER
	WALL BRACKET	MCP	MANUAL CALLPOINT
	AIR CONDITIONER		ACCESS P.C.OINT
	WALL BRACKET (CORRIDOR)		DOME CAMERA
	CONCEALED CEILING ROSE		GARDEN WALL BRACKET
	FIRE PANEL	6A	6 AMP SWITCH + SOCKET

FLOREA WING D

GENERAL NOTES

1. All dimensions are in millimeters and levels in meters unless specified otherwise.
2. Do not scale the drawing; follow written dimensions.
3. All dimensions are unfinished dimensions unless specified otherwise.
4. Any discrepancies should be brought to the notice of the Architect prior to execution of job / procuring materials at site.
5. This drawing is the property of Kapadia Associates and should not be reproduced, copied, handed over to a third party or used for any purpose other than for which it has been issued.
6. This drawing is to be read in conjunction with all relevant structural & services drawings.

KEY PLAN



REVISION INDEX

REV.NO.	DATE	DESCRIPTION
R-00	18-03-2019	
R-01	29-03-2019	SB DETAIL DIAGRAM FOR T.V ADDED CONTROL MODULE ADDED NEXT TO MCP DB LOCATION REVISED IN APARTMENT NO.4

CONSULTANTS

GOKANI CONSULTANTS
Structural Consultants
Tel : +91(022)65804400
email : info@gokaniconsultants.com

MICRO ENGINEERING
MEP Consultants
Tel : 0120-4558718
email : business@meendia.com

PBB
Planner /Landscape Architect
Tel : 079 6923054
email : landscapeindia@snq.net

STAMP & SIGN

PROJECT TITLE	PROJ.NO
PALAVA- LAKEFRONT	**L-10518**
DRAWING TITLE	DWG.NO
AR-FLOREA_D_GROUND FLOOR ELECTRICAL PLAN	**801.2**
DRAWING STAGE	REV.NO
WORKING DRAWING	**R-01**

DRAWN	CHECKED	SCALE	DATE
AD	ES	1:50	24-04-2019

KAPADIA ASSOCIATES
architecture • urban design
112-114
Peninsula Centre,Dr. S.S. Rao Road,
Parel (East), Mumbai-Pune Road,Parel East,
Mumbai 400012
Tel : 91-22-6660 2939 / 39
Fax : 91-22-6660 2944
email : mail@kapadia.net
Website : www.kapdia.net